

MMA-273034D-M5 27 – 30 GHz, 2.5W MMIC Power Amplifier


Features:

- Frequency Range: 27 – 30 GHz
- P1dB: 33 dBm
- IM3 Level: -25 dBc @ Po = 27 dBm/tone
- Gain: 26 dB
- Vdd = 6 V
- Idsq = 1100 to 1800 mA
- Input and Output Fully Matched to 50 Ω
- Output Power Detector

Applications:

- Point-to-Point Radio
- VSAT

Functional Block Diagram



Description:

The MMA-273034D-M5 is a 2.5 W GaAs pHEMT MMIC power amplifier in a compact 5 x 5 mm QFN surface mount package. The MMA-273034D-M5 provides 33 dBm of output power (P-1dB) and 26 dB of small-signal gain from 27 GHz to 30 GHz.

Electrical Specifications: Vd = 6 V, Idq = 1600 mA, Ta = 25 °C, Zo = 50 Ω

Parameter	Units	Typical Data
Frequency Range	GHz	27 - 30
Gain	dB	26
Gain Flatness	±dB	2
Input Return Loss	dB	10
Output Return Loss	dB	10
VdeR	V	0.89
VdeO @29.5GHz, @ Po = +20 dBm	V	0.85
@ Po = +33 dBm	V	0.0
Output P1dB	dBm	33
Output P3dB	dBm	34
IM3 Level ⁽¹⁾	dBc	-25
Thermal Resistance	°C / W	5.3
Total Drain Current at P1dB	mA	1600

(1) Output IP3 is measured with two tones at output power of 27 dBm / tone separated by 20 MHz.

MMA-273034D-M5

27 – 30 GHz, 2.5 W MMIC Power Amplifier

Absolute Maximum Ratings: ($T_a = 25\text{ }^{\circ}\text{C}$)*

SYMBOL	PARAMETERS	UNITS	Min.	Max.
Vd	Drain Voltage	V		6.5
Vg	Gate Voltage	V	-2.1	0
Ig	Gate Current	mA	-17	17
Pd	Power Dissipation	W		24
Pin max	RF Input Power	dBm		20
Tch	Channel Temperature	$^{\circ}\text{C}$		+150
Tstg	Storage Temperature	$^{\circ}\text{C}$		-55 to +150
Tmax	Max. Assembly Temp (20 sec max)	$^{\circ}\text{C}$		+250

*Operation of this device above any one of these parameters may cause permanent damage.

ESD Caution




High-performance RF integrated circuits are highly sensitive to electrostatic discharge (ESD) and may contain unprotected inputs and outputs. Handling and assembly should be conducted in an ESD-controlled environment. It is recommended that ESD precautions and protocols are adopted to minimise the risk of electrostatic discharge and protect product integrity.

MMA-273034D-M5


27 – 30 GHz, 2.5 W MMIC Power Amplifier

Typical RF Performance: $V_d = 6\text{ V}$, $I_{dq} = 1600\text{ mA}$, $V_g = -0.85\text{ V typ.}$, $Z_o = 50\ \Omega$


Small Signal Gain vs Frequency



Input Return Loss vs Frequency



Output Return Loss vs Frequency




MMA-273034D-M5


27 – 30 GHz, 2.5 W MMIC Power Amplifier

Typical RF Performance (cont):


Pout at P1dB and P3dB Gain Compression




Pout and Supply Current Id vs. Input Power



IM3 vs. Output Power




Detector Outputs vs. Output Power at 30 GHz



MMA-273034D-M5

27 – 30 GHz, 2.5 W MMIC Power Amplifier

Package Pin Designations:




Pin	Description
4	RF Input
21	RF Output
10	Vg
31	Vd1
29	Vd2
28	Vd3
15, 26	Vd4
11	VdeR
12	VdeO
1, 3, 5, 8, 9, 16, 17, 20, 22, 24, 25, 32, 33	Ground
2, 6, 7, 11, 12, 13, 14, 18, 19, 23, 27, 30	N/C

MMA-273034D-M5


27 – 30 GHz, 2.5 W MMIC Power Amplifier

Mechanical Drawing

The package is a 32-Lead 5 x 5 mm air-cavity QFN package that is compatible with industry standard surface mount PCB assembly processes.



BOTTOM VIEW




SIDE VIEW

The units are in [mm].

MMA-273034D-M5

27 – 30 GHz, 2.5 W MMIC Power Amplifier


Sample Application Circuit:



MMA-273034D-M5

27 – 30 GHz, 2.5 W MMIC Power Amplifier

Sample Application Board Design



Part	Description
C1, C2, C3, C4, C5, C6	1 μ F Capacitor (0603)
C7, C8, C9, C10, C11, C12	0.01 μ F Capacitor (0402)
R1, R2, R3, R4, R5, R6	10 Ω Resistor (0402)
Board Material	Rogers RO4 350B , 10 Mil Dielectric Thickness ½ oz. Copper Cladding, Copper -Filled Via Holes

MMA-273034D-M5

27 – 30 GHz, 2.5 W MMIC Power Amplifier

Biasing and Operation


The recommended bias conditions for optimum performance for the **MMA-273034D-M5** are $V_{DD} = 6.0\text{ V}$, $I_{dq} = 1600\text{ mA}$. The gate voltage (V_g) must be applied prior to the drain voltages (V_{d1} , V_{d2} , V_{d3} , V_{d4}) during power up and removed after the drain voltages during power down. A single DC gate supply connected to V_g will bias all the amplifier stages. Muting can be accomplished by setting V_g to the pinch-off voltage ($V_p = -2\text{ V}$). V_{d4} must be connected to both V_{d4} pins.

Assembly and Handling

GaAs MMICs are ESD sensitive. ESD preventive measures must be employed in all aspects of storage, handling, and assembly.

Sample Application Board Design:

Proper heatsinking and board mounting pattern with filled thermal vias are recommended for optimum performance.



RoHS Compliance



CML Micro certifies, to the best of our knowledge, that its products comply with RoHS directive (2011/65/EU), as amended by Directive (EU) 2015/863.

REACH Compliance



CML Micro certifies, to the best of our knowledge, that its products do not contain any of the banned substances specified in the SVHC list at <https://echa.europa.eu/candidate-list-table>. CML Micro are committed to ensuring the safety of products and the compliance with regulations. Publications will be updated in the event that REACH control is compromised.

Contact Information

For further information please contact your local CML sales representative.
Contact details can be found at www.cmlmicro.com.

Important notice: The information provided in this document is believed to be accurate and reliable however, CML assumes no responsibility for any errors or omissions in this document. CML reserves the right to make changes to this document at any time without notice.

The product(s) referenced within this document are not designed, authorized, or warranted for use in life support, life-critical, surgical or nuclear applications, nor in any application where the failure of the product could create a situation where personal injury or death may occur. Customers using or selling the product for such applications do so entirely at their own risk and without any recourse to CML, financial or otherwise.

CML assumes no liability for applications assistance or the design of customers' products. Customers are solely responsible for the design, validation, and testing of customer products as well as compliance with all legal, regulatory, and safety-related requirements concerning their applications.

ALL SPECIFICATIONS AND DATA ARE PROVIDED "AS IS" AND WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHTS. PRODUCTS ARE PROVIDED UNDER THE TERMS OF CML'S CONDITIONS OF SALE.

Nothing in this document or any purchase of CML products shall be construed as granting any license, whether express or implied, under any patent, copyright, trade secret, or other intellectual property right owned or controlled by CML.