

MGA-495940-02 4.4 – 5.9 GHz 10W High Efficiency Linear Power Amplifier

Features:

- 14 dB Gain
- 40 dBm P_{-3dB}
- 33 dBm Linear Pout @ 2.5 % EVM (802.11 64-QAM)
- 25 % Efficiency at 33 dBm Linear Output Power
- Fully Matched Input and Output for Easy Cascade
- +28 V Bias Voltage
- Surface Mount Package with RoHS Compliance
- MTTF > 100 years @ 85 °C ambient temperature

Applications:

- 802.16d/e WiMax
- 802.11a WLAN
- Point-To-Point Radio Applications

Description:

The MGA-495940-02 is a power amplifier with the State-of-the-Art linear power-added-efficiency between 4.4 GHz and 5.9 GHz frequency band. Based on advanced robust GaN device technology, the power-added-efficiency of this power amplifier is as high as 25 % when it outputs 2 W linear burst power with 2.5 % EVM under the 802.16d/e 64-QAM modulation schemes. The high efficiency linear power amplifier also has excellent reliability. Ideal applications include the driver and the output power stage of WiMax and WLAN infrastructures and access points. It also can be used for PTP (Point-To-Point) radio applications for this band.

Typical RF Performance: $V_{ds} = 28\text{ V}$, $I_{cq} = 80\text{ mA}$, $T_a = 25\text{ °C}$, $Z_0 = 50\text{ }\Omega$

Parameter	Units	Typical Data
Frequency Range	MHz	4400 - 5900
Gain (Typ / Min)	dB	14 / 10
Gain Flatness (Typ / Max)	±dB	1.0 / 1.5
Input Return Loss	dB	8
Output Return Loss	dB	8
Output P3dB	dBm	40
Pout @ 2.5% EVM	dBm	33
Operating Current Range	mA	100 - 400
Thermal Resistance	°C / W	5

(1) Output IP3 is measured with two tones at output power of 13 dBm / tone separated by 10 MHz.

Absolute Maximum Ratings: ($T_a = 25\text{ °C}$)*

SYMBOL	PARAMETERS	UNITS	ABSOLUTE MAXIMUM
V _{ds}	Drain-Source Voltage	V	50
I _d	Drain Current	mA	1000
I _g	Gate Current	mA	100
P _{diss}	DC Power Dissipation	W	50
P _{in max}	RF Input Power	dBm	+33
T _{ch}	Channel Temperature	°C	175
T _{stg}	Storage Temperature	°C	-55 to 150


*Operation of this device above any one of these parameters may cause permanent damage.

MGA-495940-02


4.4 – 5.9 GHz 10 W High Efficiency
Linear Power Amplifier

Typical RF Performance: $V_{ds} = 28.0\text{ V}$, $I_{cq} = 80\text{ mA}$, $Z_0 = 50\ \Omega$, $T_a = 25\ ^\circ\text{C}$


MGA-495940-02 Gain



MGA-495940-02 Return Loss



MGA-495940-02 Power



ESD Caution






High-performance RF integrated circuits are highly sensitive to electrostatic discharge (ESD) and may contain unprotected inputs and outputs. Handling and assembly should be conducted in an ESD-controlled environment. It is recommended that ESD precautions and protocols are adopted to minimise the risk of electrostatic discharge and protect product integrity.

MGA-495940-02

4.4 – 5.9 GHz 10 W High Efficiency
Linear Power Amplifier

Typical RF Performance (Cont): $V_{ds} = 28.0\text{ V}$, $I_{cq} = 80\text{ mA}$, $Z_0 = 50\ \Omega$, $T_a = 25\text{ }^\circ\text{C}$



MGA-495940-02

4.4 – 5.9 GHz 10 W High Efficiency
Linear Power Amplifier


Typical Scattering Parameters: $V_{ds} = 28.0\text{ V}$, $I_{cq} = 80\text{ mA}$, $Z_0 = 50\ \Omega$, $T_a = 25\text{ }^\circ\text{C}$

Freq (GHz)	dB(S11)	Ang(S11)	dB(S21)	Ang(S21)	dB(S12)	Ang(S12)	dB(S22)	Ang(S22)
3.00	-1.40	107.7	9.70	-24.2	-36.82	-84.6	-3.02	149.9
3.10	-1.43	104.0	9.45	-31.6	-36.75	-84.2	-2.99	146.5
3.20	-1.55	99.8	10.04	-34.2	-37.57	-88.8	-2.96	143.4
3.30	-1.59	95.4	9.97	-34.0	-37.18	-86.1	-2.92	140.0
3.40	-1.71	91.0	9.64	-38.5	-37.18	-90.2	-2.92	136.7
3.50	-1.85	85.9	10.18	-45.5	-36.27	-87.9	-2.91	133.1
3.60	-2.04	80.7	11.12	-50.2	-36.47	-87.3	-2.90	129.3
3.70	-2.24	75.1	11.94	-53.5	-35.91	-89.4	-2.91	125.5
3.80	-2.49	69.3	12.26	-56.4	-34.67	-97.1	-2.92	121.5
3.90	-2.82	63.0	12.08	-63.6	-32.84	-97.0	-2.93	117.2
4.00	-3.18	56.4	12.41	-74.4	-33.08	-103.9	-2.94	113.0
4.10	-3.59	49.4	13.13	-81.4	-31.18	-114.5	-2.97	108.4
4.20	-4.18	41.6	13.42	-86.5	-31.10	-122.3	-3.02	103.3
4.30	-4.85	32.9	13.49	-94.0	-30.28	-134.3	-3.12	98.1
4.40	-5.68	24.1	13.83	-103.1	-30.10	-144.0	-3.21	92.4
4.50	-6.71	13.8	14.49	-111.6	-30.12	-153.3	-3.35	86.2
4.60	-7.96	2.5	15.33	-119.4	-30.22	-162.3	-3.50	79.6
4.70	-9.50	-10.7	15.95	-128.3	-29.87	-168.1	-3.69	72.4
4.80	-11.54	-25.8	16.12	-140.4	-30.30	-173.8	-4.03	64.6
4.90	-14.07	-46.0	16.38	-153.6	-29.78	178.5	-4.39	56.3
5.00	-16.94	-73.0	16.36	-164.7	-29.39	172.8	-4.84	47.7
5.10	-18.97	-116.4	15.65	-176.5	-28.97	163.6	-5.28	38.4
5.20	-17.76	-159.7	15.43	169.5	-28.28	153.9	-5.73	28.6
5.30	-15.45	169.9	15.73	160.5	-28.17	145.1	-6.30	17.5
5.40	-13.63	148.1	15.38	155.0	-28.12	131.1	-6.83	5.0
5.50	-12.06	129.5	14.65	143.8	-27.83	124.6	-7.24	-8.3
5.60	-11.18	113.0	14.70	130.0	-28.76	113.2	-7.58	-22.1
5.70	-10.38	96.2	14.78	118.7	-28.35	104.0	-7.69	-36.8
5.80	-10.03	79.6	14.27	107.6	-29.12	99.2	-7.71	-51.7
5.90	-9.67	60.7	13.95	94.8	-28.90	88.3	-7.40	-66.9
6.00	-9.51	40.8	13.63	85.9	-28.53	84.1	-6.97	-81.1
6.10	-9.12	19.1	12.82	76.7	-28.38	75.2	-6.42	-94.4
6.20	-8.72	-4.0	12.43	60.7	-28.16	65.2	-5.80	-107.2
6.30	-7.99	-28.1	12.88	43.7	-28.44	48.7	-5.20	-119.3
6.40	-7.18	-51.0	12.68	29.5	-28.52	36.0	-4.67	-130.2
6.50	-6.10	-71.2	11.16	14.0	-30.40	25.9	-4.14	-139.7
6.60	-5.19	-89.6	9.25	-1.9	-31.76	11.3	-3.70	-148.7
6.70	-4.25	-106.4	6.72	-15.1	-32.64	8.9	-3.35	-157.1
6.80	-3.58	-121.0	4.30	-29.2	-34.21	7.5	-3.04	-164.8
6.90	-2.94	-134.2	3.36	-33.6	-35.34	2.6	-2.79	-171.7
7.00	-2.49	-145.6	1.77	-24.0	-35.68	5.7	-2.58	-177.8

MGA-495940-02

4.4 – 5.9 GHz 10 W High Efficiency
Linear Power Amplifier

Mechanical Information: *This Package is RoHS compliant*



All dimensions are in inches

Pin Designation (Top View)			
Pin 1 (DOT Top Left)	GND	Pin 10	GND
Pin 2	GND	Pin 9	GND
Pin 3	RF In/Vg	Pin 8	RF Out/Vdd
Pin 4	GND	Pin 7	GND
Pin 5	GND	Pin 6	GND

Application Circuit:

The evaluation board, shown in Figure 3, is fabricated with Rogers's 4003 material, 20 mil thick, 2 oz copper weight. The MGA-495940-02 shown in the center of board is a 10 watt amplifier with high gain and high linearity. For best thermal performance, the PCB requires via holes with a diameter of 20 mils placed uniformly over the center pad for thermal relief and RF ground as shown in Figure 4. The via holes underneath the package are back filled with conductive epoxy as shown in Figure 4. The choice of capacitor bypassing near the amplifier should have a short circuit resonance at the frequency of operation. A small capacitor 3.9 pf 0603 from AVX has a series resonance at 5.5 GHz and will make a good choice for the first bypass capacitor.




Figure 3 Evaluation board




Figure 4 Hole Pattern

Followed up with larger value capacitors 100pF, 1000pF and 2.2 uF can be used to maintain voltage stability under peak current conditions. The DC ground via holes should be laid out to minimized inductive returns associated with ground loops. Use of stitch ground vias holes can help control the return current and also maintain ground continuity between the top and bottom ground layers. Biasing with quarter-wave stubs at the gate and drain are shown in Figure 3. A 56 Ω resistor is added in series to the gate bias and a 2.2 nH choke is added in series to the drain bias. The effective impedance is increased which reduces the risk of low frequency oscillations.

Application Notes (cont):

802.16 256-carriers, 64-QAM @ 4.4 GHz, Pavg = 33.40 dBm @ EVM = 2.5 %

IEEE 802.16-2004 OFDM		
Frequency: 4.4 GHz	Signal Level Setting: 17.4 dBm	Ref. Level / Ext. Att: 27.4 dBm / 18 dB
Sweep Mode: Continuous	Trigger Mode: Free Run	Trigger Offset: -10 µs
Burst Type: OFDM DL Burst 6(6)	Modulation: 64QAM3/4	No Of Data Symbols: 1/2425

Result Summary						
No. of Bursts	6					
	Min	Mean	Limit	Max	Limit	Unit
EVM All Carriers	2.58	2.62	2.82	2.66	2.82	%
EVM Data Carriers	2.59	2.62		2.66		%
EVM Pilot Carriers	2.54	2.58		2.62		%
IQ Offset	0.02	0.03	17.78	0.05	17.78	%
Gain Imbalance	0.22	0.11		0.05		%
Quadrature Error	0.053	0.058		0.066		°
Center Frequency Error	35.87	35.91	± 35200	35.97	± 35200	Hz
Clock Error	-0.01	0.10	± 8	0.33	± 8	ppm
Burst Power	34.96	35.01		35.05		dBm
Crest Factor	9.26	9.33		9.40		dB
RSSI	37.98	37.98		37.98		dBm
RSSI Standard Deviation		-3.37				dB
CINR	15.70	15.70		15.74		dB
CINR Standard Deviation		16.85				dB

Application Notes (cont):

802.16 256-carriers, 64-QAM @ 4.4 GHz, Pavg = 33.40 dBm @ EVM = 2.5 %

IEEE 802.16-2004 OFDM		
Frequency: 4.9 GHz	Signal Level Setting: 16.1 dBm	Ref. Level / Ext. Att: 26.1 dBm / 17.9 dB
Sweep Mode: Continuous	Trigger Mode: External	Trigger Offset: -10 μ s
Burst Type: OFDM DL Burst	Modulation: ALL	No Of Data Symbols: 1/2425

Result Summary						
No. of Bursts	4					
	Min	Mean	Limit	Max	Limit	Unit
EVM All Carriers	2.45	2.48	2.82	2.55	2.82	%
EVM Data Carriers	2.46	2.48		2.55		%
EVM Pilot Carriers	2.34	2.41		2.54		%
IQ Offset	0.34	0.34	17.78	0.34	17.78	%
Gain Imbalance	0.12	0.12		0.12		%
Quadrature Error	0.013	0.013		0.013		°
Center Frequency Error	149.15	149.15	± 39200	149.15	± 39200	Hz
Clock Error	0.03	0.03	± 8	0.03	± 8	ppm
Burst Power	33.37	33.40		33.43		dBm
Crest Factor	9.15	9.18		9.21		dB
RSSI	36.31	36.31		36.31		dBm
RSSI Standard Deviation		- 3.06				dB
CINR	15.98	15.98		15.98		dB
CINR Standard Deviation		2.75				dB

Application Notes (cont):

802.16 256-carriers, 64-QAM @ 5.5 GHz, Pavg = 33.54 dBm @ EVM = 2.5 %


IEEE 802.16-2004 OFDM			
Frequency: 5.5 GHz	Signal Level Setting: 16.7 dBm	Ref. Level / Ext. Att: 26.7 dBm / 17.9 dB	
Sweep Mode: Continuous	Trigger Mode: External	Trigger Offset: -10 µs	
Burst Type: OFDM DL Burst	Modulation: ALL	No Of Data Symbols: 1/2425	

Result Summary						
No. of Bursts	4					
	Min	Mean	Limit	Max	Limit	Unit
EVM All Carriers	2.47	2.50	2.82	2.54	2.82	%
EVM Data Carriers	2.48	2.50		2.54		%
EVM Pilot Carriers	2.38	2.45		2.56		%
IQ Offset	0.21	0.21	17.78	0.21	17.78	%
Gain Imbalance	0.14	0.14		0.14		%
Quadrature Error	- 0.017	- 0.017		- 0.017		°
Center Frequency Error	166.88	166.88	± 44000	166.88	± 44000	Hz
Clock Error	0.02	0.02	± 8	0.02	± 8	ppm
Burst Power	33.50	33.54		33.57		dBm
Crest Factor	9.12	9.25		9.30		dB
RSSI	36.45	36.45		36.45		dBm
RSSI Standard Deviation		- 5.47				dB
CINR	15.94	15.94		15.94		dB
CINR Standard Deviation		2.20				dB

Application Notes (cont):


802.16 256-carriers, 64-QAM @ 5.5 GHz, Pavg = 33.54 dBm @ EVM = 2.5 %

IEEE 802.16-2004 OFDM							
Frequency: 5.5 GHz			Signal Level Setting: 18 dBm		Ref. Level / Ext. Att: 19.5 dBm / 17.9 dB		
Sweep Mode: Continuous			Trigger Mode: External		Trigger Offset: -10 μs		
Burst Type: OFDM DL Burst			Modulation: ALL		No Of Data Symbols: 1/2425		
Spectrum Emission Mask							
Tx Channel:		Bandwidth	3.5 MHz	Power	14.26 dBm		
Start Freq. Rel.	Stop Freq. Rel.	RBW	Freq. at Δ to Limit	Pwr Abs	Pwr Rel	Δ to Limit	
-8.750 MHz	-7.000 MHz	30 kHz	5.492988782 GHz	-38.54 dBm	-52.79 dB	-2.79 dB	
-7.000 MHz	-3.700 MHz	30 kHz	5.493044872 GHz	-38.05 dBm	-52.30 dB	-2.46 dB	
-3.700 MHz	-2.500 MHz	30 kHz	5.496326122 GHz	-26.39 dBm	-40.65 dB	-2.78 dB	
-2.500 MHz	-1.750 MHz	30 kHz	5.497504007 GHz	-22.05 dBm	-36.31 dB	-4.44 dB	
1.750 MHz	2.500 MHz	30 kHz	5.502495994 GHz	-23.01 dBm	-37.27 dB	-5.39 dB	
2.500 MHz	3.700 MHz	30 kHz	5.503281250 GHz	-25.19 dBm	-39.44 dB	-3.53 dB	
3.700 MHz	7.000 MHz	30 kHz	5.506899039 GHz	-38.57 dBm	-52.83 dB	-3.20 dB	
7.000 MHz	8.750 MHz	30 kHz	5.507011218 GHz	-38.94 dBm	-53.20 dB	-3.20 dB	



Application Notes (cont):

Typical constellation response for 802.16 Pavg = 32.5 dBm @ 2.5 % EVM, 5.9 GHz



RoHS Compliance



CML Micro certifies, to the best of our knowledge, that its products comply with RoHS directive (2011/65/EU), as amended by Directive (EU) 2015/863.

REACH Compliance



CML Micro certifies, to the best of our knowledge, that its products do not contain any of the banned substances specified in the SVHC list at <https://echa.europa.eu/candidate-list-table>. CML Micro are committed to ensuring the safety of products and the compliance with regulations. Publications will be updated in the event that REACH control is compromised.

Contact Information

For further information please contact your local CML sales representative.
Contact details can be found at www.cmlmicro.com.

Important notice: The information provided in this document is believed to be accurate and reliable however, CML assumes no responsibility for any errors or omissions in this document. CML reserves the right to make changes to this document at any time without notice.

The product(s) referenced within this document are not designed, authorized, or warranted for use in life support, life-critical, surgical or nuclear applications, nor in any application where the failure of the product could create a situation where personal injury or death may occur. Customers using or selling the product for such applications do so entirely at their own risk and without any recourse to CML, financial or otherwise.

CML assumes no liability for applications assistance or the design of customers' products. Customers are solely responsible for the design, validation, and testing of customer products as well as compliance with all legal, regulatory, and safety-related requirements concerning their applications.

ALL SPECIFICATIONS AND DATA ARE PROVIDED "AS IS" AND WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESSED OR IMPLIED, INCLUDING BUT NOT LIMITED TO ANY IMPLIED WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT OF INTELLECTUAL PROPERTY RIGHTS. PRODUCTS ARE PROVIDED UNDER THE TERMS OF CML'S CONDITIONS OF SALE.

Nothing in this document or any purchase of CML products shall be construed as granting any license, whether express or implied, under any patent, copyright, trade secret, or other intellectual property right owned or controlled by CML.